


LH 108/800

Diplexer for Mobile Telephone (800 – 2400 MHz) and Car Radio (0 – 108 MHz)

DESCRIPTION

- Diplexer for simultaneous operation of mobile telephone and car radio on a common mobile telephone antenna.
- Excellent wide-band coverage 800 – 2400 MHz.
- Extremely small dimensions.
- Quick installation using dual-adhesive pad provided.
- FME-connections on antenna and transceiver terminals
 - CRC (M10 x 0.75) connection on the car radio terminal.
- 1 m or 5 m Procom 75 Ohm car radio cable available as an option.




ORDERING DESIGNATIONS

TYPE	PRODUCT NO.
LH 108/800	200 000 779

SPECIFICATIONS

ELECTRICAL	
MODEL	LH 108/800
FREQUENCY	Mobile telephone: 800 MHz – 2400 MHz Car radio : 0 - 108 MHz
MAX. INPUT POWER	25 W
INSERTION LOSS	0 - 108 MHz : ≤ 1.0 dB 800 - 2400 MHz : ≤ 0.7 dB
ISOLATION	Low to high port: ≥ 45 dB
IMPEDANCE	Transceiver : 50 Ω Car radio : 75 Ω
MECHANICAL	
TEMP. RANGE	-30° C → +70° C
CONNECTORS	TX/RX: FME Car radio: CRC-Connector (M10 x 0.75) Antenna : FME
DIMENSIONS (W x H x D)	50 x 21 x 60 mm
WEIGHT	Approx. 68 g
ACCESSORIES	Car radio cable Type 1 m CRC (length 1 m) Type 5 m CRC (length 5 m)

TYPICAL RESPONSE CURVES



INSTALLATION NOTES

1. The 50 Ω cable between antenna and diplexer should be kept as short as possible (preferably not more than 1 m).
2. Some communication antennas have insufficient height to ensure satisfactory broadcast reception. Only antenna whips with a height of at least 25 cm are acceptable.
3. Tuning: The antenna is tuned for best SWR at the operating frequency as usual. The filter is factory-tuned and ready for installation.



PROCOM A/S reserve the right to amend specifications without prior notice.

08/06/2010