

PRO-RPS-4-N 4-Channel RX Power Splitter



DESCRIPTION:

- ★ Low power, compact 4-channel power splitter/combiner.
- ★ The splitter covers the frequency range from 50–1000 MHz.
- ★ Almost no ripple in loss and isolation over the entire frequency range.



SPECIFICATIONS:

ELECTRICAL	
FREQUENCY RANGE	50–1000 MHz
MAX. INPUT POWER	2 W
INSERTION LOSS (above 6 dB)	< 1.5 dB
ISOLATION OUTPUT TO OUTPUT	> 20 dB
IMPEDANCE	Nom. 50 Ω
SWR	< 1.3
MECHANICAL	
TEMP. RANGE	-30° C → +60° C
CONNECTORS	N-female
DIMENSIONS (L x W x H)	89 x 39 x 29 mm
WEIGHT	Approx. 200 g

